


KNX power supply 320 mA with integrated choke



Specification	Order No.	Packing unit	PS	EAN
 DRA	2122 00	1	66	4010337023227

Power supplies for supplying KNX devices with bus voltage.

Features

- Output with integrated choke to supply KNX bus lines.
- Output DC 30 V to supply additional devices.
- Rated current can be flexibly split up amongst outputs.
- Reset button.
- Short-circuit-proof.
- Overvoltage protection.
- Open circuit-proof.
- Suitable for operation in systems with emergency power supply.
- Isolated signal contact for operating message and diagnostic message.
- Two KNX power supplies of the same type to increase performance can be switched directly in parallel.

Technical data

Rated voltage	
- AC:	AC 200 to 240 V, 50/60 Hz
- DC:	DC 240 to 250 V
Output voltage	
- KNX line:	DC 28 to 31 V SELV
- Additional output:	DC 30 V
Signal output	
- AC switching voltage:	AC 12 to 230 V
- Switching voltage DC:	DC 2 to 30 V
- Switching current:	5 mA to 2 A
Connections	
- KNX:	Connection and junction terminal
- Mains voltage:	Screw terminals
Connections:	max. 4 mm ²

Illustrations are similar and may deviate from originals.

Ambient temperature: -5 °C to +45 °C

Output current: 320 mA

Short-circuit current: max. 1 A

Notes

- Installation on DIN top-hat rail.
 - VDE approval in accordance with EN 60669-1, EN 60669-2-1.
-

Scope of supply

- KNX connection and junction terminal included in the scope of supply.
-

Dimensions

Modular widths (MW): 4
