GIRA Data sheet

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

eNet Radio Energy Sensor, 1-gang Mini



Specification	Order No.	Packing unit	PS	EAN
	5471 00	1/5	02	4010337774365

Features

- The eNet radio energy sensors enable the radio transmission of voltage, electricity, and energy values to the eNet server.
- Logging electricity and voltage of the connected device.
- Calculation of effective output, reactive power, apparent power, and active electrical energy.
- Event-controlled or time-controlled transmission of measurement value telegrams to the eNet server.
- Time synchronisation with the eNet server.

Technical data

Rated voltage: AC 230 V, 50/60 Hz

Rated load current: 16 A

Ambient temperature: -5 °C to +45 °C

Measurement range

Electricity: 0 mA to 16 A
Electrical power: 0 to 3680 W
Energy consumption: 0 to 99999 kWh

Radio frequency.: 868.3 MHz

Range (free field): approx. 100 m

Notes

- Installation in device box, surface-mounted housing, or in an installation adapter.
- Radio approval is valid for EU and EFTA countries.

GIRA Data sheet

catalogue.gira.com

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

Dimensions in mm

Ø 53

H 23