PWM DIMMERS + CONTROLS

Analog 1-10 V PWM Dimmer Din Rail 1-Channel





1 channel LED dimmer. Control is either via a 100 k $\Omega\square$ potentiometer, 1–10 V control voltage source or with a push button (PUSH-DIM function). The output voltage corresponds to the supply voltage of 12–24 V.

PROLED ANALOG 1-10 V DIMMER DIN RAIL 1-CHANNEL Manual

1.8 MB 🕹



> 5 years warranty information

TECHNICAL DATA

12–24 V
12 A
1
1–10 V,100 k Ω potentiometer, PUSH-DIM
1
12–24 V DC
-20° C till +45° C
35 x 67 x 112 mm
0,1 kg

PRODUCT TYPES

order code	description	
L51515	ANALOG 1-10 V DIN RAIL PWM DIMMER 1-CHANNEL	

 $@ \ \mathsf{MBN} \ \mathsf{GmbH} \\$

