Fiber Optic Fault Locator VFL



KE850 EasyPoint

Applications

The compact design of the visual fault locator is very suitable for daily use in all fiber optic applications e.g. in the field, in industrial environment as well as in laboratory.

- To check singlemode/multimode optical fiber and other fiber optic components on faults
- Patching of fibers
- Detects too strong curved glass fibers





| Parame | eter | | | |
|--|--|--|--|--|
| Fiber types | | Singlemode, Multimode, POF | | |
| Wavelength | | 655 nm (visible) | | |
| Laser protection class | | Class II | | |
| Optical output power | | max. 1 mW / 0 dBm | | |
| Operation mode | | Continuous Wave; Pulsed Mode, frequency 2 - 3 Hz | | |
| Range | | Singlemode: > 4 km; Multimode: > 2.5 km | | |
| Ferrule | | 2.5 mm suitable for DIN, E2000, FC, SC, ST with ceramic coating to avoid interferences (optional Adapter for 1.25 mm or POF) | | |
| Operation time (pulsed mode) | | 40 hours | | |
| Battery type | | 2 x AAA Alkaline batteries | | |
| Weight | | 70 g batteries included | | |
| Dimensions | | Length 157 mm, diameter 12 mm, Etui: 180 x 70 x 22 mm (B x T x H) | | |
| Operating temperature | | -10° + 45° C | | |
| Storage temperature | | -10° + 70° C | | |
| ■ Spar ■ One ■ Instru Access | re dust cap battery pack uction manual sories (not included) rent Adapters avapter 2.5 mm to | Your Dealer vailable | | |
| - Ada | apter POF | | | |
| - Ada - Ada | apter POF | Artikelbezeichnung | | |
| - Ada - Ada Artikel-Nr. 0.49100 | Typ A KE850 EasyPoint F | Artikelbezeichnung Fiber optic fault locator, batteries, etui | | |
| - Ada | . Typ A KE850 EasyPoint F Fiber Adapter A | Artikelbezeichnung | | |

Included in delivery

- Packed in etui style packaging
- Spare dust cap
- One battery pack
- Instruction manual



Accessories (not included)

- Different Adapters available
 - Adapter 2.5 mm to 1.25 mm
 - Adapter POF



| Artikel-Nr. | Тур | Artikelbezeichnung | | |
|-------------|-----------------|--|--|--|
| 0.49100 | KE850 EasyPoint | Fiber optic fault locator, batteries, etui | | |
| 1400070 | Fiber Adapter | Adapter for 2.5 mm to 1.25 mm | | |
| 1400078 | Fiher Adanter | Adapter for 2.5 mm to POF | | |



