

LED Driver 10 W

LED-10



LED Driver 10 W with built-in dimming function for one or more LED luminaires (150–700 mA) or LED strips (12/24 V DC) for up to 10 W. The product can be controlled wirelessly via the app or through other products from Plejd.

- Dimmable 1–100 %.
- Two inputs for local control, using for example a momentary push button or motion sensor.
- Time functions, such as astro/time schedule.
- Scenes from phone, tablet, or push button.

Install the product in the appliance box behind the push button/box lid or secure it with a Mounting clip (MNT-01, not included) on the wall or DIN rail.


Load (CC)

150 mA	1–4 W
350 mA	1–9 W
500 mA	1–10 W
700 mA	1–10 W

Use only for LED loads (DC).

Load (CV)

12 V (DC)	0–8 W
24 V (DC)	0–10 W



MAINS ELECTRICITY

230 VAC/50 Hz, max 0.15 A

STANDBY POWER

0.3 W

EXTERNAL OPERATING TEMPERATURE

-20 to +35 °C

DIMENSIONS

46x46x18 mm

CABLE AREA

Connections: 0.5–4.0 mm²

PROTECTION

Overtemperature software
Short circuit protection

POWER FACTOR (PF)

0.6

UOUT

3–28 V DC

RADIO

2.4 GHz mesh
Bluetooth®
<10 dBm

RADIO RANGE

Approx. 10 m indoors.
The Plejd mesh technology extends the range by allowing the units to communicate with each other.

